

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru

Цифровой фазовый измеритель VICTOR 4300



Описание:

4300	
Function	Three Phase, AC current, AC voltage, AC leakage current, direct test of phase sequence, transformer groups, inductive, capacitive circuit discrimination; indirect test of power factor and power
Clamp size	Acuminate current clamp: 7.5mm×13mm (4300)
Weight	Main Unit about 550g (with battery) , acuminate current clamp about 170g×3, round current clamp about 185g×3, test line about 250g
Measurement range	AC Voltage: 0.00 V~600V
	AC Current: 0.0mA~20.0A
	Phase: 0~360°
Power	DC9V alkaline batteries (1.5V AA×6)
Meter size	Length, Width, Height: 196mm×92mm×54mm
Sampling Rate	About 2 times/second
Data storage	99 sets
Display Mode	LCD display, 240dots×160dots
Data Hold	Press HOLD key to keep data, "DH" symbol appears
Automatic Shutdown	Automatic shutdown about 15 minutes later after launching to reduce battery consumption
Backlighting	Suitable for dark place and nightly use
Test Line Length	1.5m
Working Temperature and Humidity	-10℃~40℃; below 80%Rh
Storage Temperature and Humidity	-10℃~60℃; below 70%Rh
Input impedance	Testing voltage the input impedance is 2MΩ