

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru

Утечка зажима VICTOR 7100B



Описание:

Model 7100B	
Function	ACA, leakage current, load current on-line test, suitable for electricity leakage patrol inspection of down hole and outdoor multi-conductor thick cable
Power Source	DC 3.7V chargeable lithium battery, USB charging portal, working continuously for 10h
Display Mode	Four digital LCD display, backlight function, suitable for dark place
Tested Line Diameter	Φ168mm Conductor, cable or 168mm×245mm bus bar
Measurement Range	Current: AC 10mA~9999A(50~60Hz automatically)
Resolution	10mA
Current Accuracy	10mA~999A, ±2%±5dgt
	1000A~2999A, ±3%±5dgt
	3000A~9999A, ±4%±5dgt
Size of Insulation Rod	300mm
Instrument Size	Length width thickness 310mm×270mm×52mm
Line Voltage	bare wire test 1000V below, less than 10kV with a safety insulation sheath wire. (operating with an insulation rod)
Automatic Shutdown	About 15mins after startup, the instrument will be automatically shut down to reduce battery consumption
Instrument Mass	Instrument: 496g(include battery); Total mass: 2.3kg (including insulation rod and instrument box)