

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru

VICTOR 26 / 26H Многофункциональные калибраторы процессов

Идентификатор предмета № 26 / 26H



Project		Model		
		Performance		
Source	DC millivolt	Range	-5 ~ 110mV	-5 ~ 110mV
		Accuracy= ±(% of the set value+% of range)	0.01%+0.01%	0.01%+0.01%
		Resolution	1uV	1uV
	DC voltage	Range	-1 ~ 11V	-1 ~ 11V
		Accuracy= ±(% of the set value+% of range)	0.01%+0.01%	0.01%+0.01%
		Resolution	10uV/0.1mV	10uV/0.1mV
	DC current	Range	0 ~ 33mA	0 ~ 33mA
		Accuracy= ±(% of the set value+% of range)	0.01%+0.01%	0.01%+0.01%
		Resolution	1uA	1uA
	Sink current	Range	0 ~ 33mA	0 ~ 33mA
		Accuracy= ±(% of the set value+% of range)	0.01%+0.01%	0.01%+0.01%
		Resolution	1uA	1uA
	Resistance	External power	5 ~ 28V	5 ~ 28V
		Range	0 ~ 4KΩ	0 ~ 4KΩ
		Accuracy= ±(% of the set value+% of range)	0.01%+0.01%	0.01%+0.01%
	Thermocouple	Resolution	0.01Ω/0.1Ω	0.01Ω/0.1Ω
		Range	R/S/K/E/J/T/B/N/L/U	R/S/K/E/J/T/B/N/L/U
		Accuracy	0.4°C	0.4°C
	RTD	Resolution	0.1°C/1°C	0.1°C/1°C
		Range	Pt100/Pt200/Pt500/	Pt100/Pt200/Pt500/
		Accuracy	0.2°C	0.2°C
	Frequency (Hz)	Resolution	0.1°C	0.1°C
		Range	1Hz ~ 110KHz	1Hz ~ 110KHz
		Accuracy	±2words	±2words
Frequency (CMP)	Resolution	0.01Hz/1Hz/0.1KHz/2KHz	0.01Hz/1Hz/0.1KHz/2KHz	
	Range	60 ~ 1200 CPM	60 ~ 1200 CPM	
	Accuracy	±2words	±2words	
Pulse	Resolution	1CPM	1CPM	
	Frequency	1Hz ~ 10KHz	1Hz ~ 10KHz	
	Range	1 ~ 100000cyc	1 ~ 100000cyc	
	Accuracy	±2words	±2words	
	Resolution	1cyc	1cyc	

	Switch	Range	1Hz ~ 110KHz	1Hz ~ 110KHz
		Accuracy	±2个字	±2个字
	Pressure	Resolution	0.01Hz/1Hz/0.1KHz/2KHz	0.01Hz/1Hz/0.1KHz/2KHz
		Range	Depends on the pressure module	Depends on the pressure module
	DC millivolt	Accuracy= ±(% of the set value+% of range)	Depends on the pressure module	Depends on the pressure module
		Resolution	5 digit display	5 digit display
	DC voltage	Range	-5 ~ 550mV	-5 ~ 550mV
		Accuracy= ±(% of Reading+ % of Range)	0.01%+0.01%	0.01%+0.01%
	DC current	Resolution	1uV/10uV	1uV/10uV
		Range	-0.5 ~ 35V	-0.5 ~ 35V
	Resistance	Accuracy= ±(% of Reading+ % of Range)	0.01%+0.01%	0.01%+0.01%
		Resolution	0.01Ω/0.1Ω	0.01Ω/0.1Ω
	Thermocouple	Range	R/S/K/E/J/T/B/N/L/U	R/S/K/E/J/T/B/N/L/U
		Accuracy	0.7°C	0.7°C
	RTD	Resolution	0.1°C/1°C	0.1°C/1°C
		Range	Pt100/Pt200/Pt500/	Pt100/Pt200/Pt500/
	Frequency (Hz)	Accuracy	0.4°C	0.4°C
		Resolution	0.1°C	0.1°C
	Frequency (CMP)	Range	3Hz ~ 50KHz	3Hz ~ 50KHz
		Accuracy	±2words	±2words
	Switch	Resolution	0.01Hz	0.01Hz
		Range	180~3000000 CPM	180~3000000 CPM
	Pressure	Accuracy	±2words	±2words
		Resolution	1CPM	1CPM
	Loop power supply	Range	CLOSE/OPEN	CLOSE/OPEN
		Threshold	200 ~ 300Ω	200 ~ 300Ω
	Continuity beeper	Range	Depends on the pressure module	Depends on the pressure module
		Accuracy= ±(% of Reading+ % of Range)	Depends on the pressure module	Depends on the pressure module
	HART	Resolution	5 digit display	5 digit display
		Range	0 ~ 500Ω	0 ~ 500Ω
	Other functions	Accuracy	≤50Ωsound	≤50Ωsound
		Resolution	0.01Ω	0.01Ω
	Communication function	Range	24V	24V
		Accuracy	±10%	±10%
	Characteristic	The maximum current	22mA	22mA
		Safety	EN61010-1: 2001	EN61010-1: 2001
	Withstand voltage	Backlight	√	√
		Auto Power-off	√	√
	Insulation	Charging function	√	√
		Room temperature display	√	√
	EMC	Battery detection	√	√
		The ramp signal	√	√
	Authentication	Communication function	RS232 serial communication, can realize	RS232 serial communication, can realize
		Display	3.2" TFT screen	3.2" TFT screen
	Power supply	Power supply	4×1.5V AA Alkaline battery	4×1.5V AA Alkaline battery
		Size	206 × 97 × 60 mm	206 × 97 × 60 mm
	Weight	Weight	about 633g	about 633g
		Standard Quantity Per Carton	6pcs	6pcs
	Standard Carton Measurement	Standard Carton Measurement	530mm*405mm*310mm	530mm*405mm*310mm
		Standard Carton Cross Weight	12.6kg	12.6kg

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru