

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru

Цифровые динамометрические ключи NG-30/60/135/200/340

Код товара № NG-30/60/135/200/340.



Specifications

| Model | NG-030 | NG-060 | NG -135 | NG -200 | NG-340 |
|------------------------------------|---|---|---|---|---|
| Min. Resolution | 0.01 | | 0.1 | | |
| Max. Operation Range (N.m) | 30N.m/22.12ft t.lb/265.5in.lb /305.91kgf.cm | 60N.m/44.25ft.l b/531.04in.lb/6 11.82kgf.cm | 135N.m/99.57ft .lb/1195in.lb/13 76.61kgf.cm | 200N.m/147.5 ft.lb/1770in.lb /2039.43kgf.c m | 340N.m/250ft .lb/3009in.lb/ 3467.03kgf.c m |
| Square Drive (inches) | 3/8 | | 1/2 | | |
| Measured Torque Range (N.m) | 1.5~30 | 2~60 | 6.75~135 | 10~200 | 17~340 |
| Length(mm) | 420 | | 535 | | 655 |
| Accuracy | Clockwise: $\pm 2\%$ counterclockwise: $\pm 2.5\%$ | | | | |
| Data storage capacity | 100 | | | | |
| Operation mode | Peak hold mode (P) /Real-time mode (T) | | | | |
| Unit | N.m \、 in.lb \、 ft.lb \、 kgf.cm | | | | |
| Ratchet head type | Double-side ratchet head | | | | |
| Number of ratchet gear | 36 | | | | |
| Button | 5 | | | | |
| Battery | AA battery $\times 2$ | | 1.5V (No. 5 battery) | | |
| Operation temperature | $-10^{\circ}\text{C}\sim 60^{\circ}\text{C}$ | | | | |
| Storage temperature | $-20^{\circ}\text{C}\sim 70^{\circ}\text{C}$ | | | | |
| humidity | No condensation to 90% | | | | |
| Drop test height | 1 meter | | | | |
| Vibration test condition | 10G | | | | |
| Life time test | 10000 times | | | | |

Note:

*1 when you use the torque wrench within the 10% to 100% of the whole range, we can ensure the accuracy. Torque accuracy is normal value. To make sure accuracy, we suggest to make calibration once a year.

*2 To use a special transmission line to transfer data to computer.

*3 Life testing including level and vertical test.

*4 "Once" means put force from 0 N.m to max. Force and then return back to 0N.m.

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Волгода (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://victor.nt-rt.ru/> || vtd@nt-rt.ru