

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31



<https://victor.nt-rt.ru/> || vtd@nt-rt.ru

Цифровые клещи VICTOR 610C, 610B



Цифровой зажим VICTOR VC610C VC610B, ручной измеритель переменного/постоянного тока с автоматическим выбором диапазона, функцией True RMS, размером ЖК 35*24 мм.

Описание:

Model	610B		610C	
Function	Range	Accuracy	Range	Accuracy
ACV	4V/40V/400V	± (1.0%+10)	2V/20V/200V	± (1.0%+10)
	750V	± (1.0%+12)	750V	± (1.0%+12)
DCV	400mV/4V/40V/400V	± (0.5%+7)	200mV/2V/20V/200V	± (0.5%+7)
	1000V	± (1.0%+6)	1000V	± (1.0%+6)
Resistance	400 Ω /4k Ω /40k Ω /400k Ω /4M	± (1.0%+5)	200Ω/2kΩ/20kΩ/200kΩ	± (1.0%+5)
	40MΩ	± (1.2%+10)	40MΩ	± (1.2%+10)
ACA	40A/400A/1000A	± (2.5%+10)	2A/20A/200A/1000A	± (2.5%+10)
DCA	40A/400A/1000A	± (2.5%+10)		
Frequency	(0~10) MHz	± (0.3%+3)		
Capacitance	4nF	± (5.0%+40)		
	40nF/400nF/4uF/40uF/400uF/1mF	± (5.0%+10)		
Diode test	✓		✓	
Continuity alarm	✓		✓	
Data hold	✓		✓	
Low voltage display	✓		✓	
Auto power off	✓		✓	
Overload Protection	✓		✓	
NCV	✓		✓	
True RMS	✓		✓	
Display	Max. display 4000, update 3 times/s		Max. display 2000, update 3 times/s	
Polarity indicate	Cathode auto display		Cathode auto display	
Overload indicate	OL indicating on the LCD		OL indicating on the LCD	
Low battery display	 indicating on the LCD		 indicating on the LCD	
Operation temperature	0°C~40°C, less than 75%RH		0°C~40°C, less than 75%RH	
Storage temperature	-10°C~50°C, less than 80%RH		-10°C~50°C, less than 80%RH	
Battery type	(Size AAA) 1.5V×2		(Size AAA) 1.5V×2	
Size	198*73*37mm		198*73*37mm	
Weight	About 250g		About 250g	

Архангельск (8182)63-90-72
 Астана (7172)727-132
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89
 Иваново (4932)77-34-06

Ижевск (3412)26-03-58
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16

Пермь (342)205-81-47
 Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13

Сургут (3462)77-98-35
 Тверь (4822)63-31-35
 Томск (3822)98-41-53
 Тула (4872)74-02-29
 Тюмень (3452)66-21-18
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31